

# 1.5W (15W Replacement) Bright White (3000K) E17 Base T7 Intermediate Appliance LED Light Bulb

## Features

- Product life: 13.6-years (based on 3-hours/day)
- Light appearance: 3000K (Bright White)
- Energy used: 1.5-Watt
- **Ideal usage:** Refrigerator



## Specifications

<b>Item Number</b>	<b>Item Length (In)</b>	<b>Item Width (In)</b>	<b>Bulb Shape</b>
BPT7N/LED/HDRP	2.1	0.9	T7
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Bulb Finish</b>	<b>Technology</b>
Tubular	E17	Clear	LED - SMD
<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>	<b>Color Accuracy (CRI)</b>	<b>Color Temperature (CCT)</b>
80	53.33	80	3000
<b>Life Hours</b>	<b>Life Years</b>	<b>Voltage</b>	<b>Replacement</b>
15000	13.7	120	15
<b>Annual Energy Cost</b>	<b>Energy Efficiency</b>	<b>Energy Used (Wattage)</b>	<b>Battery Operated</b>
0.18	90.0%	1.5	NO
<b>Pack Quantity</b>	<b>Smart</b>	<b>Portable</b>	<b>Dimmable</b>
1	No	NO	NO
<b>Hardwire</b>	<b>Enclosed Fixture Rated</b>	<b>Safety Location</b>	<b>CEC Compliant</b>
NO	YES	Damp	Not Regulated
<b>Warranty Years</b>			
2			