

8 Ft. 40W (75W Replacement) Daylight (5000K) FA8 Base T12 Direct Replacement (Type A) LED Linear Tube (2-Pack)

Features

- Works with most magnetic or electronic ballasts so no rewiring or electrician is required
- Plug and play Type A installation lowers labor costs when converting T12 fixtures to LED
- Uses up to 45% less energy than a 75W fluorescent tube, cutting utility costs fixture by fixture



Specifications

Item Number	Item Length (In)	Item Width (In)	Bulb Shape
T1296/850/A/LEDG2/2	93.8	1.6	T12
Bulb Base	Brightness (LUMENS)	Color Accuracy (CRI)	Color Temperature (CCT)
FA8	5000	80	5000
Life Hours	Life Years	Voltage (V)	Replacement (Wattage)
35000	32.0	120-277	75
Energy Used (Wattage)	Battery Operated	Pack Quantity	Smart
40	No	2	No
Portable	Dimmable	Enclosed Fixture Rated	Safety Location
No	No	No	Damp
CEC Compliant			
Not Regulated			