

# 4 Ft. 18W Selectable White G13 Base (T8 And T12 Replacement) Ballast Bypass (Type B) LED Linear Tube (2-Pack)

## Features

- Ballast bypass installation requires direct wiring for more efficient operation and less maintenance over time
- Shatter-resistant and mercury-free, no special disposal is required
- Flicker-free, instant ON illumination at full brightness
- **Ideal usage:** Office, Garage or Warehouse Lighting



## Specifications

<b>Item Number</b>	<b>Item Length (In)</b>	<b>Item Width (In)</b>	<b>Bulb Shape</b>
T4815/4CCTBLEDD/2CAN	47.7	1.2	T8
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Tube Type</b>	<b>Technology</b>
Tubular	Bi-Pin	Type B	LED - SMD
<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>	<b>Color Accuracy (CRI)</b>	<b>Color Temperature (CCT)</b>
1800	100.0	80	3000 4000 5000 6500
<b>Life Hours</b>	<b>Life Years</b>	<b>Voltage</b>	<b>Replacement</b>
50000	45.7	120-277	32
<b>Annual Energy Cost</b>	<b>Energy Used (Wattage)</b>	<b>Battery Operated</b>	<b>Pack Quantity</b>
2.17	18	NO	2
<b>Smart</b>	<b>Portable</b>	<b>Dimmable</b>	<b>Hardwire</b>
No	NO	NO	NO
<b>Enclosed Fixture Rated</b>	<b>Safety Location</b>	<b>Energy Star</b>	<b>CEC Compliant</b>
YES	Damp	No	Not Regulated