

# 4 Ft. 18W (32W Replacement) Bright White (3000K) G13 Base Direct Replacement (Type A) (T8 Replacement) LED Linear Tube (10-Pack)

## Features

- Works with most electronic ballasts, no rewiring is required
- Shatter-resistant and mercury-free, no special disposal is required
- Flicker-free, instant ON illumination at full brightness
- **Ideal usage:** General purpose lighting



## Specifications

<b>Item Number</b>	<b>Item Length (In)</b>	<b>Item Width (In)</b>	<b>Bulb Shape</b>
T848/830/LED/10	47.8	1.0	T8
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Bulb Finish</b>	<b>Tube Type</b>
Tubular	Bi-Pin	White	Type A
<b>Technology</b>	<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>	<b>Color Accuracy (CRI)</b>
LED - SMD	1800	100.0	80
<b>Color Temperature (CCT)</b>	<b>Life Hours</b>	<b>Life Years</b>	<b>Voltage</b>
3000	35000	32.0	120-277
<b>Replacement</b>	<b>Annual Energy Cost</b>	<b>Energy Efficiency</b>	<b>Energy Used (Wattage)</b>
32	2.17	43.8%	18
<b>Battery Operated</b>	<b>Pack Quantity</b>	<b>Smart</b>	<b>Portable</b>
No	10	No	No
<b>Dimmable</b>	<b>Hardwire</b>	<b>Enclosed Fixture Rated</b>	<b>Safety Location</b>
No	No	Yes	Damp
<b>Energy Star</b>	<b>CEC Compliant</b>		
No	Not Regulated		