

8 Ft. 43W (59W Replacement) Cool White (4000K) FA8 Base (T8 Replacement) Ballast Bypass (Type B) LED Linear Tube

Features

- Converts your existing fluorescent fixture to LED techNology
- Two 4-foot segments snap together to form an extra-long 8-foot lamp
- Ballast bypass requires direct wiring, offering longer installation but more efficient operation and less maintenance



Specifications

| Item Number | Item Length (In) | Item Width (In) | Bulb Shape |
|-------------------------|---------------------|------------------------|-----------------------|
| T96/840/B/LED | 96 | 1 | Т8 |
| Bulb Type | Bulb Base | Bulb Finish | Tube Type |
| Tubular | FA8 | White | Туре В |
| Technology | Brightness (LUMENS) | Lumen Efficiency (LPW) | Color Accuracy (CRI) |
| LED - SMD | 5000 | 116.28 | 80 |
| Color Temperature (CCT) | Life Hours | Life Years | Voltage |
| 4000 | 50000 | 45.7 | 120-277 |
| Replacement | Annual Energy Cost | Energy Efficiency | Energy Used (Wattage) |
| 59 | 5.18 | 27.1% | 43 |
| Battery Operated | Pack Quantity | Smart | Portable |
| No | 1 | No | No |
| Dimmable | Hardwire | Enclosed Fixture Rated | Safety Location |
| No | No | Yes | Damp |
| CEC Compliant | Warranty Years | | |
| Not Regulated | 5 | | |
| | | | |